


Joystick click™

1. Introduction



Joystick click™ is an accessory board in **mikroBUS™** form factor. It's a compact and easy solution for adding joystick to your design. It features **AS5013** Hall IC as well as **N50P105** miniature magnetic joystick module. Joystick click™ communicates with the target board microcontroller via **mikroBUS™** I²C (SDA, SCL), INT, RST and CS lines. The board is designed to use 3.3V power supply only. LED diode (GREEN) indicates the presence of power supply.


2. Soldering the headers

Before using your click™ board, make sure to solder 1x8 male headers to both left and right side of the board. Two 1x8 male headers are included with the board in the package.



1

2




Turn the board upside down so that bottom side is facing you upwards. Place shorter pins of the header into the appropriate soldering pads.

3



Turn the board upward again. Make sure to align the headers so that they are perpendicular to the board, then solder the pins carefully.




4. Essential features

Joystick click™ with its **AS5013** IC and **N50P105** represents smart navigation key concept based on contactless, magnetic movement detection. The **AS5013** includes five integrated Hall sensing elements which are monitoring the movement of the magnet, incorporated into the joystick, and provides directly the x and y coordinates via I²C output. An integrated mechanical push button is also built in joystick.

3. Plugging the board in

Once you have soldered the headers your board is ready to be placed into desired mikroBUS™ socket. Make sure to align the cut in the lower-right part of the board with the markings on the silkscreen at the mikroBUS™ socket. If all of the pins are aligned correctly, push the board all the way into the socket.



click™
BOARD
www.mikroe.com

Joystick click Manual
ver. 1.00



